DIGITAL DIFFERENTIAL ANALYZER
CRC 101

The Difference Analyzer: A Simple Differential Equation Solver

Introduction. The difference analyzer is a new type of analog computing machine which permits the solution of sets of non-linear as well as linear ordinary differential equations by a simplified stepwise integration method.

The analog computer solution of a typical set of two ordinary differential equations

$$(1) \quad \frac{dx}{dt} = \psi_1(x, y, t) \quad \frac{dy}{dt} = \psi_2(x, y, t)$$

is discussed.

In the electromechanical analog computers under consideration here, two voltages

$$(2) \quad \begin{aligned} \frac{dX}{d\tau} &= \frac{a_x}{a_t} \psi_1 \left[\frac{1}{a_x} X, \frac{1}{a_y} Y, \frac{1}{a_t} \tau \right] \\ \frac{dY}{d\tau} &= \frac{a_y}{a_t} \psi_2 \left[\frac{1}{a_x} X, \frac{1}{a_y} Y, \frac{1}{a_t} \tau \right] \end{aligned}$$

are obtained as functions of the shaft rotations X , Y , and τ proportional to x , y , and t , respectively, through the use of universal function potentiometers¹ and resistive summing networks. The scale factors a_x , a_y , and a_t must be chosen so that neither the shaft rotations nor the voltages (2) exceed their physically possible operating ranges.

At the beginning of each computation, the τ , X , and Y shafts are set to initial settings corresponding to the given initial values of t , x , and y ; usually $\tau = 0$ at the beginning of a computer run. If, now, the machine can be made to establish the additional relations

$$(3) \quad X = \int_0^\tau \frac{dX}{d\tau} d\tau, \quad Y = \int_0^\tau \frac{dY}{d\tau} d\tau$$

between the shaft rotations X , Y , and the voltages $\frac{dX}{d\tau}$, $\frac{dY}{d\tau}$, then *all these*

quantities must vary in the manner prescribed by the differential equations (1) and may be recorded as solutions of the problem.

In machines of the electromechanical differential analyzer type, the integrations (3) are performed continuously, for instance by means of rate servos whose output speed must be accurately proportional to an input voltage. The construction of the electromechanical integrators requires great care and constitutes a major portion of the cost of a differential analyzer.

In the difference analyzer, the integrations are performed by stepwise displacements of the shafts corresponding to the variables in question. The new machine permits rapid, reasonably accurate (one to three percent) solutions at minimum expense, since no servomechanisms or amplifiers need be used. Various applications and refinements of the difference analyzer are also discussed.

The Difference Analyzer. In the difference analyzer, a new analog computer first described by the writer,² some of the errors and particularly the high costs inherent in the electromechanical integrators are avoided at the expense of some additional computing time.

Fig. 1 illustrates the principle of the difference analyzer. The desired initial values of the variables τ , X , and Y , are set up as shaft rotations, as before. Then these shaft rotations are varied *step by step* by amounts $\Delta\tau$, ΔX , and ΔY , respectively, in a manner prescribed by the given mathematical relations (1). The voltages proportional to the derivatives (2) are obtained as functions of the shaft rotations by means of resistive networks and function potentiometers in the manner indicated in Fig. 2.

FIG. 1. Simple difference analyzer.

The values of the derivatives $\frac{dX}{d\tau}$ and $\frac{dY}{d\tau}$ are measured accurately by means of *linear comparison potentiometers* connected to the same supply voltage as the computing networks used to compute $\frac{dX}{d\tau}$ and $\frac{dY}{d\tau}$. If the scale factors a_x , a_y , and a_t have been chosen correctly, the displacements of the comparison potentiometers will be equal to $\frac{dX}{d\tau}$ and $\frac{dY}{d\tau}$, respectively, when the galvanometers shown in Fig. 1 indicate zero current.

The increments ΔX and ΔY of the dependent machine variables, corresponding to a small increment $\Delta\tau$ of the independent machine variable τ will be approximately

$$(4) \quad \Delta X = \frac{dX}{d\tau} \Delta\tau, \quad \Delta Y = \frac{dY}{d\tau} \Delta\tau.$$

The multiplications in (4) may be performed simply by means of step-down gears which multiply the respective displacements of the comparison poten-

tiometer shafts by the constant parameter $\Delta\tau$. The resulting shaft rotations ΔX and ΔY are taken as the increments corresponding to an increment $\Delta\tau$ in the displacement of the τ shaft.

The actual computation proceeds by the iteration of the following two very simple steps.

(i) *Computation of Correct Derivatives.* With the clutches shown in Fig. 1 disengaged, the operator balances the galvanometers by adjusting the comparison potentiometers. The respective displacements of the two potentiometers are now proportional to $\frac{dX}{d\tau}$ and $\frac{dY}{d\tau}$. Note that these settings do *not* have to be read by the operator.

FIG. 2. Example of a circuit generating a voltage proportional to a function of two shaft rotations τ and Y by means of function potentiometers and resistive summing networks.

(ii) *Mechanical Addition of Increments.* The operator next engages the clutches so that the shafts of the $\frac{dX}{d\tau}$ and $\frac{dY}{d\tau}$ potentiometers are connected to the respective variable shafts through suitable gear trains. Next, the $\frac{dX}{d\tau}$ potentiometer is reset to its center, or zero position. This involves a displacement proportional to $\frac{dX}{d\tau}$ which, with the clutch engaged, is imparted to the X shaft through a gear ratio $1:\Delta\tau$ in such a manner that the correct increment

$$\Delta X = \frac{dX}{d\tau} \Delta\tau$$

is added to the displacement X . Similarly, an increment ΔY corresponding to (4) is added to the displacement of the Y shaft when the $\frac{dY}{d\tau}$ potentiometer is reset to zero.

The τ (independent variable) shaft is simply advanced by a specified constant amount $\Delta\tau$.

The operator then disengages the clutches and the whole process is repeated for the newly obtained values of τ , X , and Y . It is readily seen that the dependent variables X and Y must vary according to the prescribed equations (4); the process just described constitutes a *stepwise integration* of the differential equations (1).

It may be shown that the error involved in this stepwise integration *as such* could be made as small as desired by using sufficiently small time increments $\Delta\tau$.³ Actually, the accuracy of the machine is determined by the accuracy of the dial settings and by the tolerances of the resistive computing networks. Random errors in dial settings or potentiometer linearity tend to cancel in the course of the integration process. Certain errors due to imperfect computing networks, however, may be integrated and may thus increase during the integration.

Because of the various errors involved in the computation, an analog computer attempting to solve a single differential equation of the form

$$(5) \quad \frac{dY}{d\tau} = f(\tau, Y)$$

for the correct voltage Y will actually solve a slightly different equation

$$\frac{d\bar{Y}}{d\tau} = f(\tau, \bar{Y}) + A(\tau, \bar{Y}),$$

where $A(\tau, \bar{Y})$ is the *derivative error* assumed to be bounded in absolute value by a positive quantity δ . It may be shown³ that the absolute value error

$$\epsilon = |Y - \bar{Y}|$$

in the solution Y will satisfy the relation

$$(6) \quad \epsilon \leq \delta |\tau - \tau_0| e^{M|\tau - \tau_0|},$$

where $|\tau - \tau_0|$ is the computing time and where

$$|f(\tau_1, Y_1) - f(\tau_1, Y_2)| \leq M |Y_1 - Y_2|$$

for τ_1 , Y_1 , and Y_2 in the region under consideration.

In the case of a difference analyzer set up to solve equation (5), it is possible to write

$$(7) \quad \delta \leq \lambda_1 + \mu_1 + \mu_2 \Delta\tau.$$

Here λ_1 is the absolute value of the greatest possible error in $\left. \frac{d\bar{Y}}{d\tau} \right]_{\tau, \bar{Y}}$ as compared to $f(\tau, \bar{Y})$ due to the computing elements used to produce $f(\tau, \bar{Y})$; μ_1 is the absolute value of the largest possible derivative error incurred in setting the machine variable $\bar{Y}$ to a new value. $\mu_2 \Delta\tau$ is a measure of the largest derivative error incurred by replacing $f(\tau, \bar{Y})$ by the constant value of $f(\tau_i, \bar{Y}_i)$ corresponding to $\tau = \tau_i$ and $\bar{Y} = \bar{Y}_i$ in the i th step of the stepwise integration. The relations (6) and (7) constitute an estimate of the upper bound of the error made by a difference analyzer in the solution of the given differential equation (5).

Example of An Error Estimate. Consider the solution of the machine equation $\frac{dY}{d\tau} = Y$ with $Y = 1$ for $\tau = \tau_0 = 0$ in the interval $0 \leq \tau \leq \tau_1$. This is a typical problem unfavorable for analog computer solution because of its "unstable" monotonically increasing solution. Here $M = 1$.

If this problem is solved on a typical *difference analyzer* with

$$\lambda_1 \leq 0.005 \left. \frac{dY}{d\tau} \right|_{\text{MAX}} = 0.005e^{\tau_1}, \mu_1 \leq 0.002 \left. \frac{dY}{d\tau} \right|_{\text{MAX}} = 0.002e^{\tau_1}$$

one has

$$\mu_2 \leq \left. \frac{d^2Y}{d\tau^2} \right|_{\text{MAX}} = e^{\tau_1}.$$

In this case, the difference analyzer will be as accurate as a typical differential analyzer with $\delta \leq 0.01 e^{\tau_1}$ if one chooses

$$\Delta\tau \leq 0.003.$$

For large values of τ_1 , it might pay in this particular problem to divide the interval under consideration into subintervals, all but one of which would yield smaller values of μ_2 .

Practical Results. A small difference analyzer was used by the writer to solve Euler's equations of motion for a rigid body.⁴ As a test problem, the system of differential equations

$$(8) \quad \frac{dX}{d\tau} = Y, \quad \frac{dY}{d\tau} = -X$$

with $X = 0$ and $Y = 1$ for $\tau = 0$, which has the well known solutions

$$X = \sin \tau \text{ and } Y = \cos \tau$$

was solved on the difference analyzer. A computer setup for the system (8) is shown in Fig. 3.

The construction of resistive networks with an accuracy of better than 0.2 percent is well known to the art and quite easily possible with relatively low-cost components. Helical potentiometers were used in the setup of Fig. 3. For a 45-step integration from $\tau = 0$ to $\tau = \pi/4$, better than one percent overall accuracy in terms of full scale readings was attained at less than one-third the cost of a comparable differential analyzer.

Refinements. The computing networks of a difference analyzer may be interconnected by means of patchcords so that a *flexible multi-purpose computer* results.

The advantages inherent in the low cost of the difference analyzer become apparent particularly when non-linear differential equations are to be solved. Again, higher order differential equations can always be reduced to systems of first-order equations by introducing the derivatives as new variables.

The possibility of introducing new variables simply by means of new dependent variable shafts in the difference analyzer suggests the use of such "mechanical transformations" to simplify complicated computer setups and to improve scale factors with resulting increases in accuracy. Fig. 4 shows how

FIG. 3. Difference analyzer setup for the system

$$\frac{dX}{d\tau} = Y, \quad \frac{dY}{d\tau} = -X.$$

FIG. 4. Mechanical amplification and function generation. The Z-shaft is set to the correct value by means of a meter or comparison potentiometer (no integration).

a voltage Z corresponding to some function

$$Z = Z(X, Y, \tau)$$

of the independent and dependent variables is brought out to a terminal from some point of the computing networks, read by means of a meter or comparison potentiometer, and re-entered into the machine by means of a Z-shaft. Potentiometers on this Z-shaft may then generate desired functions of the new variable Z .

This process will be used most often to make a new larger voltage corresponding to X available in the computer or to change impedance levels in the computing networks (mechanical amplification). It should be noted carefully that such mechanical amplification and function generation does *not* constitute an integration (no derivative of Z is used to reset the Z -shaft). All mechanical transformations of this type should be performed *before* the integrations. It may be expedient to use knobs of a different color for shafts whose settings are not derived from integrations.

The operator will then begin each step of the computation by balancing the potentiometers used for mechanical amplification and will then proceed by balancing the potentiometers used for integration in the manner outlined further above. While mechanical transformations do introduce extra shafts which must be set at each step of the computation, their use may result in substantial improvements and simplifications in the computer setup.

The Automatic Difference Analyzer. Whereas the difference analyzer, as described above, may be operated by relatively unskilled personnel, even the simple operations required for the stepwise computation method could be mechanized through the use of very simple servomechanisms, thereby permitting completely automatic operation of the equipment. Fig. 5 shows the block diagram of an automatic difference analyzer for the solution of the equation

$$\frac{dX}{d\tau} = f(X, \tau).$$

The computing networks function as before. The comparison potentiometer becomes the follow-up potentiometer of a servomechanism which balances the potentiometer by making the shaft displacement equal to $\frac{dX}{d\tau}$.

FIG. 5. Automatic difference analyzer. The solenoid clutch and the resetting relay are operated periodically by a switch on the τ -shaft.

The servo shaft is then reset to zero by grounding one servo input by means of a resetting relay.

During this process, the resetting clutch shown is engaged by means of a solenoid in such a manner that the correct increment ΔX is added to the displacement of the X -shaft through a gear train. At the same time, the $\Delta \tau$ shaft displacement is increased by a specified amount by means of a step motor; the resetting relay as well as the solenoid clutch are actuated by a switch on this shaft.

The entire process is repeated until stopped by a limit switch or by the operator at some desired time τ ; each step must allow sufficient time for the potentiometer shafts to assume their new positions. It should be noted here that the frequency response of the servomechanism used will *not* affect the accuracy of the computation. The process described constitutes a completely automatic stepwise integration of the given differential equations by means of components such as simple relay servos which are cheaper than the integrators used in a comparable differential analyzer.

Conclusions. The difference analyzer seems to be an easily constructed, reliable, and useful instrument of about slide rule accuracy and should be well adapted to the solution of sets of complicated non-linear differential equations in smaller laboratories and educational institutions. In such cases, the cost of a differential analyzer of comparable accuracy and reliability would often be prohibitive, and the equations would yield only to tedious numerical integration. If still greater accuracy is desired, a difference analyzer solution will provide a convenient check on conventional numerical analysis. F. J. MURRAY has also suggested the use of stepwise integration methods based on non-linear extrapolation in order to decrease the number of steps needed and to increase the accuracy of the machine.

Acknowledgments. The difference analyzer was first developed by the writer in the research laboratories of the Curtiss-Wright Corporation, Airplane Division, Columbus, Ohio, under a contract with the Applied Physics Laboratory, Johns Hopkins University, Silver Spring, Maryland. A model was constructed in the Physical Research Unit, Boeing Airplane Company, Seattle, Washington, while the writer was on loan to the latter organization under a temporary agreement with the Curtiss-Wright Corporation.

The writer wishes to thank Mr. G. H. STONER of the Boeing Airplane Company for his interest in this work, and Messrs. G. BROWN, F. KATES, and A. MOWERY for their very able assistance in the construction of the machine.

Acknowledgment is also due Mr. E. C. WELLS of the Boeing Airplane Company, and Mr. R. BLAYLOCK, of the Curtiss-Wright Corporation for their permission to publish this material.

GRANINO A. KORN

Lockheed Aircraft Corp.
Burbank, Calif.

¹G. A. KORN, "Design and construction of universal function generating potentiometers," *Rev. Sci. Instruments*, v. 21, 1950, p. 77.

²G. A. KORN, "The general difference analyzer," Curtiss-Wright, Airplane Division, Report P537-V-46, 1948.

³L. BIEBERBACH, *Differentialgleichungen*. Berlin, Springer, 1930, p. 27.

⁴G. A. KORN, "Application of a new analog computer to the integration of Euler's equations for a spinning body," Boeing Aircraft Company, Document no. D9969, June 3, 1949.