QUARTERLY OF APPLIED MATHEMATICS

Vol. XVII

APRIL, 1959

No. 1

AN APPLICATION OF ALGEBRAIC TOPOLOGY: KRON'S METHOD OF TEARING*

BY

J. PAUL ROTH

The Institute for Advanced Study, Princeton, N. J.

It is well known that an important class of problems in numerical analysis can be interpreted as "electrical" network problems [1, 2, 3]. These analogues have formed the basis of many analogue and digital methods of solution of certain partial and ordinary differential equations. The most extensive and diverse such interpretations have undoubtedly been made by Kron [4-9]. Furthermore, it has been pointed out by von Mises [10] that the network approach to numerical analysis offers promise for the numerical solution of physical problems for which classical methods, in spite of great effort, have been unavailing—problems for which future research demands a numerical answer. See also the recent work of Birkhoff and Diaz [11] utilizing network methods in non-linear problems. An excellent example of a successful attack by network methods is given by Oppenheim [12, 13]. See also the provocative work of Branin [14].

We shall here consider not the problem of devising topological models for physical problems, but the network problem *per se*. We begin with a resumé of its history.

1. History of the network problem. Kirchhoff, as a student in Neumann's seminar, made the first comprehensive investigation of the electrical network problem, publishing his results in 1845 and 1847 [15]. Kirchhoff proved the existence of a solution to the "purely resistive" network problem. In formulating the problem he was perhaps the first to write down the incidence relations of a 1-dimensional complex. Maxwell [16] pointed out (1865), however, that Kirchhoff's formulation omitted the concept of potential. Maxwell remedied this omission and devised two methods for solving the network problem effectively, now termed Maxwell's *mesh-* and *node-pair-methods* of solution. (The two methods may be described in Fig. 1 as that of inverting L' and Y' .) In 1923 Weyl [17] presented another proof of Kirchhoff's result giving deeper insight into its topological character. His 1932-33 lecture notes refer to currents and voltages as contravariant and covariant vectors. Eckmann's 1945 paper [18] gave further insight into the problem.

In 1933 and 1934 [19, 20] Kron utilized the tensor calculus to fit in the concept of "impedance" of stationary and non-stationary networks into the topological frame-work. This advanced the application of tensor calculus from field problems to circuit problems. Kron published a treatise on these developments for non-stationary networks in 1938 [21]

*Received July 26, 1957; revised manuscript received February 21, 1958. This material was presented in lectures at the University of California in Berkeley and Los Angeles, Princeton University, The University of Pennsylvania, and General Electric Co. in Schenectady in the years 1954-1956.

and for stationary network in 1939 [22]. See also [23]. Figure 1 is an interpretation of Kron's view of the network problem; he had each mapping and viewed the problem in its general form. Actually the concepts of tearing and interconnecting appeared in these publications: in the process of writing down the "equations of performance" of a system. The idea of interconnecting solutions did not appear explicitly until 1953 [8]. Kron's formulation of the network problem has been studied by many investigators [24-28].

An algebraic topological formulation of the network problem and a proof of the validity of the method of tearing were given by the author [29-32]. A condition called *power definiteness* [31] was shown to be sufficient for the existence of a solution to the network problem; it is shown in the present paper that the proof given in [31] actually utilized the weaker condition termed "ohmicness". In fact, ohmicness (Sec. 2) turns out to be a necessary and sufficient condition for the existence and uniqueness of the generalized network problem, the problem actually encountered in tearing.

Section 3 treats the question: what systems can be represented as a network problem? The answer is any system of linear equations can be so represented (but *not* necessarily in a way suitable for efficient tearing.) In Sec. 4 tearing is briefly described. The invariance of power under tearing is demonstrated in Sec. 5. Section 6 describes Kron's "orthogonal" method of solution of networks. Section 7 describes the explicit construction of the solution of the network problem via tearing. Section 8 describes K -partitioning: this is a way due to Kron of solving a system of linear equations which in general requires fewer operations than the customary inversion of a matrix. Sections 9, 10, and 11 give explicit solutions to three network problems, counting the required number of operations for tearing, K -partitioning and standard inversion methods.

2. Necessary and sufficient conditions for the existence of a solution to Kron's problem. We give a more general formulation of the network problem than in [31]. A *network* is defined as a 1-dimensional regular complex. Let K then be a network and let L be a transformation of its group $C^1(K)$ of 1-chains into $C_1(K)$ its group of 1-cochains, over the complex coefficient field. Then K and L define the diagram shown in Fig. 1. Here $H^1(K)$ is the first homology group, $P^0(K)$ is the group of 0-boundaries, the image of $C^1(K)$ under the boundary operator; $H_1(K)$ is the first cohomology group and $P_0(K)$ the group of 0-cochains modulo the kernel of the coboundary operator δ . Further C is the natural homomorphism of $H^1(K)$ into $C^1(K)$ [$C^1(K)$ may be considered as $H^1(K, K^0)$, where K^0 is the 0-skeleton], while C_i is the dual transformation of $C_1(K)$ into $H_1(K)$; ∂ denotes the boundary operator (strictly speaking, the boundary operator *followed* by the projection of $C^0(K)$ into $P^0(K)$). Finally $L' = C_iLC$, $Y = L^{-1}$ and $Y' = \partial Y\delta$. The network problem then is: Given arbitrary elements I' of $P^0(K)$ and e' of $H_1(K)$ to find elements J of $C^1(K)$ and V of $C_1(K)$ such that $\partial J = I'$, $C_iV = e'$ and $V = LJ$, i.e. to find a general expression of V and J in terms of arbitrary e' and I' and the transformation of the above diagram. A pair (J, V) satisfying these conditions for given I' , e' is termed a *solution*. In [31] it was shown that a solution always exists and is unique if L is power definite. Professor N. E. Steenrod pointed out, however, that the proof actually utilized only the following weaker condition:

Definition. Let V be a vector space of complex dimension n and V_* , the dual space of linear functions on V . A linear transformation of V into V_* is termed *ohmic* if for each non-zero v in V , $(Lv)_i \cdot (v) \neq 0$, i.e. L is ohmic if it never maps a non-zero vector v into a function which annihilates v . This condition is more general than power definiteness, which in turn is a more general condition than positive definiteness.

Professors R. J. Walker and T. S. Motzkin of Cornell University and UCLA have suggested the following interpretation of ohmicness: Let $L = M + iN$ where $M = (L + L^*)/2$ and $N = (L - L^*)/2i$ are hermitian. Splitting these into their real and imaginary parts $M = M_1 + iM_2$, $N = N_1 + iN_2$ we set

$$A = \begin{bmatrix} M_1 & -M_2 \\ M_2 & M_1 \end{bmatrix} \quad B = \begin{bmatrix} N_1 & -N_2 \\ N_2 & N_1 \end{bmatrix}.$$

Then L is ohmic if and only if the two quadric hypersurfaces

$$x_i A x = 0 \quad x_i B x = 0$$

have no real intersection.

The introduction of an isomorphism L between a vector space V and its dual V_* is equivalent to the introduction of an inner product in V for if $v, w \in V$, we may define $v \cdot w$ as $(Lv) \cdot w$. If L is ohmic this inner product is not necessarily commutative. If V is a vector space over the reals and L is positive definite then the usual properties of an inner product are enjoyed. Although the results below guarantee that tearing is valid under the more general condition of ohmicness, all the applications to date have been, to the author's knowledge, for L positive definite. In Kron's model of Schrödinger's equation, however, L is ohmic but not positive definite.

Theorem 1. If L is ohmic, the network problem has one and only one solution. For let $i' \in H^1(K)$ and $L'i' = 0$; then $i' \cdot L'i' = 0$. Letting $i = C'i'$ we see $i' \cdot L'i' = i \cdot Li \Rightarrow i = 0$ and since C is an isomorphism i' must also be zero so that the kernel of L' is zero and L' is thus 1-1. Similarly Y' is shown to have an inverse and $J = C(L')^{-1}e' + Y\delta(Y')^{-1}I'$ and $V = LJ$ will constitute a unique solution. Uniqueness follows by the same argument as in [31].

Kron's approach to networks (whether stationary or not) is always from the following point of view: He considers not just a single network with its impedance tensor, but the set of all possible networks into which it can be transformed through the group of tearing—and interconnecting—transformations. His method of tearing consists in deducing from the "equations of state" or the "equations of solution" for one element of the set (usually a simple one) the "equations of state" or "of solution" for any other element in the set by a routine procedure governed by the induced transformations. Stated another way, a given system is torn apart, solved in pieces, then the piecewise solutions are interconnected to yield the solution for the whole.

We wish to find a condition on L such that a solution will exist for *all* networks K compatible with L (we say K is *compatible* with L if the dimension of $C^1(K)$ is the same as the dimension of L); i.e. regardless of how the network is hooked together we still wish to be guaranteed the existence of a solution: we term this the *generalized network problem* of Kron.

Theorem 2. A necessary and sufficient condition that the generalized network problem have a solution is that L be ohmic.

Theorem 1 establishes the sufficiency; for necessity, let v be a non-zero 1-chain such that $v \cdot Lv = 0$; now construct a network where v is a cycle, then it is clear that L' will not be an isomorphism.

3. What systems can be represented as a network problem? This question is of

especial interest to those concerned with explicit numerical solutions of their problems (see [33]). If tearing is a shortcut method for solving the network problem, can it be used to solve arbitrary non-singular systems of linear equations? The answer is that there is an infinity of network problems which can represent a given such system but there is no *a priori* method for picking out a "good" such representation. We give here one such representation (which does no good whatsoever from the viewpoint of computations). Let $Lx = b$ be a non-singular transformation (L can be a "function" of x and b), L of dimension n . Let K be a network in which the natural mapping $C: H^1(K) \rightarrow C^1(K)$ is an isomorphism; we then consider L as a transformation from $C^1(K)$ into $C_1(K)$ and thus $C_1LC = L'$ is also an isomorphism. (K consists of n 1-spheres with exactly a single point in common, a "bouquet" of 1-spheres.) By Theorem 1 the network problem automatically has a solution, but now we have no "room" to tear (see Sec. 4). We must invert L' which is the same as inverting L . Any non-singular system of finite difference equations can thus be interpreted as a network problem, which harmonizes with von Mises' use of the term. The more usual mode of viewing this is the "all" junction-pair of equivalent network. This result is related to that of Lyusternik [2] and Bode [34] on the question of realizability.

In Kron's approach one attempts to represent not a given set of equations but rather a *physical system* by means of a topological model. While the topological model can be made to produce a purely algebraic system, the process is not reversible: the topological model contains more structure, more information, than a purely algebraic system. It has been recently suggested by Professor Synge (Princeton University Colloquium Lecture, Feb. 7, 1956) that certain fundamental problems in quantum mechanics contain inherent topological structure which must be understood for their solution.

While the all-resistance or resistance-capacitance models of Poisson's equations are widely used, not so well known are Kron's more subtle topological models for a large class of partial differential equations of mathematical physics (both classical and quantum physics) such as the field equations of Maxwell; the wave-equation of Schrödinger; the Navier-Stokes equations of compressible, viscous flow; the elastic field, etc., [3-9], [35], [36].

4. Tearing. Let K and K^* be regular 1-complexes and φ a continuous map of K^* into K which induces an isomorphism Q of $C^1(K^*)$ on $C^1(K)$. Figure 1 of [32] depicts the maps induced by φ on the reduced homology and cohomology sequences of K and K^* . If L is an ohmic isomorphism between $C^1(K)$ and $C_1(K)$ then $L^* = Q_*LQ$ defines an ohmic transformation of $C^1(K^*)$ on $C_1(K^*)$. Thus if K is compatible with the tensor L so is K^* and thus associated with L is the collection of all K^* for which there exists a transformation φ inducing an isomorphism of the 1-chain groups. Note that φ is not necessarily a topological map. In [32] a description is given of how a network problem in K defines a network problem in K^* and how computation of the solution for K^* allows for the deduction of the solution for K .

First we shall discuss an ancillary question—the invariance of the power under tearing and interconnection—then we shall give an explicit description of the construction of a solution via tearing and conclude with some concrete examples where tearing gives quicker results.

In recent unpublished papers Kron has solved eigen-value problems of large-scale physical systems and linear programming problems by means of tearing. He has likewise utilized tearing to obtain analytic solutions of certain large-scale problems, e.g. involving

resonant frequencies of nuclear reactors. Indeed the savings in straightforward numerical solutions seem to be trivial compared to these developments [37].

5. The invariance of the power under tearing [33]. Let $J \in C^1(K)$ and $V = LJ$. The power is defined as the product $V \cdot J$. Explicitly, $V \cdot J$ in matrix notation is $V_i^* \cdot J = J_i^* L_i^* J$; (power as here defined is the sum of the *dissipative* $(V_i J^* + V_i^* J)/2 = J_i^* (L + L^*) J$ and *reactive* $(V_i J^* - V_i^* J)/2i = J_i^* (L - L^*)/2i$ power, the latter multiplied by i).

Theorem. Power is invariant under tearing and interconnection. For let φ be a map of network K^* on network K which induces an isomorphism Q of $C^1(K^*)$ on $C^1(K)$. The induced transformation

$$C^1(K^*) \xrightarrow{Q} C^1(K)$$

on the group of 1-cochains is then

$$C_1(K^*) \xleftarrow{Q^1} C_1(K).$$

Let J^* be an element of $C^1(K^*)$: the power corresponding to this element is $V^* \cdot J^*$. But if $J^* = QJ$ and $V = Q_i V^*$ then the corresponding power in K is $V \cdot J = (Q_i V^*) \cdot (Q^{-1} J^*) = V^* \cdot J^*$, q.e.d.

This theorem settles a problem which apparently long has plagued the literature in network theory, namely the invariance of the power under the transformations induced by interconnection. The concept of tearing as a form of transformation has been emphasized by Kron [36]. Still many investigators, including Kron, have attempted to deduce the law of transformation from the invariance of the power.

The fundamental geometrical fact about tearing and interconnecting is that there is a one-to-one correspondence between the branches of the two networks: the transformation φ of interconnecting and its "inverse", tearing, explicitly establish this correspondence. If the complexes are simplicial, we may restrict the transformation of interconnection to be a simplicial map: but the really essential feature is that it establishes this 1-1 correspondence between branches: expressed another way, *the transformation φ shall induce an isomorphism of the 1-chain groups.* In algebraic topology the laws of transformation of 1-chains and 1-cochains (currents and voltages) are well known and completely understood (see [38]): the underlying geometrical transformation dictates the transformations (P, Q, R, P_i, Q_i, R_i) of [32] in the algebraic superstructure.

And thus the invariance of the power is a consequence of these transformations and not a cause of them. The other approach therefore was forced somehow to smuggle in the assumption of the invariance of the power. For instance, le Corbeiller [28] in his fine little book on Kron's method employs very detailed but circuitous reasoning in this attempt.

6. Kron's "Orthogonal" method of solution of networks. Preparatory to the construction of an explicit solution via tearing we must first consider Kron's so-called "orthogonal" method of solving networks. Maxwell's mesh method and node-pair

FIG. 1.

method of solving networks in modern terminology amounts to inverting L' or Y' respectively (see Fig. 1); the method we describe here stays within the spaces of $C^1(K)$ and $C_1(K)$ and although in general this method requires exactly as much work as the mesh or node-pair method it gives a new twist to the subject, to pave the way for tearing.

It may be seen that the following method gives a solution. Let $C^1(K)$ be written as the direct sum of its cycle group R^1 plus some other group, S^1 , chosen at one's pleasure:

$$C^1(K) = R^1 \dot{+} S^1.$$

Let a basis be selected for R^1 and S^1 , so that an element J of C^1 can be written in coordinate form

$$J = \begin{bmatrix} i \\ I \end{bmatrix},$$

i , I being the coordinates of J in R^1 , S^1 . Let us choose the "same" basis for $C_1(K)$ (see [32], also Cartan's cosimplex, [39], p. 39): this choice of basis effects a splitting of $C_1(K)$ say

$$C_1(K) = R_1 \dot{+} S_1$$

(of the four groups R^1 , S^1 , R_1 , S_1 , only R^1 is natural).

Let an element V of $C_1(K)$ be written therefore

$$V = \begin{bmatrix} e \\ E \end{bmatrix}$$

with e , E , elements of R_1 and S_1 , or rather e , E , being the coordinates of V in R_1 , S_1 for the bases chosen. Note that R_1 , which corresponds to the dual basis for R^1 , is disjoint from the subgroup of coboundaries and that in general S_1 is *not* the coboundary group. Nevertheless the natural homomorphism of R_1 into $H_1(K)$ is an isomorphism. (The reader should now refer the argument to Fig. 1.) Thus an element e' of $H_1(K)$ may be pulled back to an element e of R_1 . Likewise an element I' of $P^0(K)$ can be pulled back under to an element I of S^1 . Thus we have elements e , I , such that $C_e e = e'$ and $\partial I = I'$. (Note that in some actual problems such an e is frequently given in the original specification of the problem). We shall write the ohmic transformation between $C_1(K)$ and $C^1(K)$ in the form

$$\begin{bmatrix} i \\ I \end{bmatrix} = \begin{bmatrix} Y_1 & Y_2 \\ Y_3 & Y_4 \end{bmatrix} \begin{bmatrix} e \\ E \end{bmatrix}. \quad (6.1)$$

We shall call this the *first normal form*. The solution may now be obtained by inverting Y_4 (Y_4 is ohmic by heredity)

$$E = Y_4^{-1}(I - Y_3 e). \quad (6.2)$$

Then i may be obtained as $Y_1 e + Y_2 E$. The above formula for E will be termed the "orthogonal" form of the solution. This is the form of the solution we will use for the torn system in the next section.

Alternatively if we write the ohmic transformation in the form inverse to 6.1, termed the *second normal form*,

$$\begin{bmatrix} e \\ E \end{bmatrix} = \begin{bmatrix} L_1 & L_2 \\ L_3 & L_4 \end{bmatrix} \begin{bmatrix} i \\ I \end{bmatrix}. \quad (6.3)$$

This is the form assumed by the problem for the interconnected system *after* interconnection [see Eq. (7.5)]. In this form a solution is effected by inverting L_1 : then

$$i = L_1^{-1}(e - L_2 I),$$

$$E = L_3 i + L_4 I.$$

7. Explicit construction of solution of network problem via tearing. An important consideration not previously discussed is a convenient method of construction of the solution via tearing. We shall be working with *coordinates* which will transform then in the direction *opposite* to the transformations of the vector spaces themselves. Let K^* be a torn version of K so that there exists a regular map φ (simplicial map if complexes K and K^* are simplicial) inducing an isomorphism φ^* of 1-chain groups.

We shall split $C^1 = C^1(K)$ and $C_*^1 = C^1(K^*)$ into the following direct sums

$$C_*^1 = M_* + P_*,$$

$$C^1 = M^0 + M^1 + P.$$

Here M_* is the subspace of cycles of C_*^1 ; M^0 is the isomorphic image of M_* under the transformation φ^* induced by φ , M^1 is a subspace of cycles whose direct sum with M^0 "fills out" the subspace of cycles. P_* and P likewise fill out C_*^1 and C^1 respectively, but are so chosen that $\varphi^*(M^1 + P) = P_*$, and thus φ^* splits in the following fashion

	M^0	$M^1 \quad P$	
M_*	U	O	
P_*	O	Q	$U = \text{identity}$

It is clear that such choices can be made.

Let bases be chosen for each of these subspaces. Then in coordinate form, for i_* , I_* elements of M_* , P_* and i^0 , i^1 , I elements of M^0 , M^1 , P , φ^* takes the explicit form

$$\begin{pmatrix} i_* \\ I_* \end{pmatrix} = \begin{pmatrix} U & O \\ O & Q \end{pmatrix} \begin{pmatrix} i^0 \\ i^1 \\ I \end{pmatrix} \quad (7.1)$$

Let the "same" bases be chosen for $C_1 = C_1(K)$ and $C_1^* = C_1(K^*)$ inducing thus a splitting of each of these spaces: $C_1 = M_0 + M_1 + P_1$, $C_1^* = M^* + P^*$; let e_0 , e_1 , E and e^* , E^* denote elements of these subspaces in the order implied. Then the induced isomorphism φ_* on the 1-cochain spaces is written

$$\begin{pmatrix} e_0 \\ e_1 \\ E \end{pmatrix} = \begin{pmatrix} U & O \\ O & Q \end{pmatrix} \begin{pmatrix} e^* \\ E^* \end{pmatrix}. \quad U = \text{identity} \quad (7.2)$$

Suppose now that the K^* network problem is written Kron's "orthogonal" fashion, with respect to the basis chosen for K^*

$$\begin{pmatrix} i_* \\ I_* \end{pmatrix} = \begin{pmatrix} Y_1^* & Y_2^* \\ Y_3^* & Y_4^* \end{pmatrix} \begin{pmatrix} e^* \\ E^* \end{pmatrix}. \quad (7.3)$$

This is the first form for the "orthogonal" system [see Eq. (6.1)]. The solution is obtained by inverting $Y_4^\#$. Let $L^\# = (Y_4^\#)^{-1}$ and $I^\# = I_4 - Y_4^\# e^\#$. Then

$$E^\# = L^\# I^\#. \quad (7.4)$$

(For the purposes of interconnecting, however, it is, of course, quite immaterial what manner is employed to compute $E^\#$ in the form $L^\# I^\#$). Equation (7.4) represents a solution of the $K^\#$ network problem: we now construct the solution of that of K via the interconnection transformations. Utilizing successively (7.2), (7.4) and (7.1),

$$\begin{bmatrix} e_1 \\ E \end{bmatrix} = Q_1 E^\# = Q_1 L^\# I^\# = Q_1 L^\# Q \begin{bmatrix} i^1 \\ I \end{bmatrix}. \quad (7.5)$$

We now split $Q_1 L^\# Q$ into its component parts

$$\begin{bmatrix} e_1 \\ E \end{bmatrix} = \begin{bmatrix} L_1 & L_2 \\ L_3 & L_4 \end{bmatrix} \begin{bmatrix} i^1 \\ I \end{bmatrix}. \quad (7.6)$$

This is the second form for the "orthogonal" system [see Eq. (6.3)]. The work that remains to be done therefore, after the interconnection, is the inversion of L_1 , which may be termed the elimination of the newly created cycles. Thus we write as the final solution

$$i^1 = L_1^{-1}(e_1 - L_2 I), \quad (7.7)$$

$$E = L_3 i^1 + L_4 I. \quad (7.8)$$

Of course (7.7) may be substituted directly into (7.8) to obtain $E = (L_4 - L_3 L_1^{-1} L_2) I + L_3 L_1^{-1} e_1$ but from a computational viewpoint it is advisable *not* to do so. In the next section we shall consider in detail the question of the number of operations performed. Reviewing the actual steps taken for solving by means of tearing we see that the following operations had to be performed.

- A) In (7.3) $Y_4^\#$ was inverted: $(Y_4^\#)^{-1} = L^\#$.
- B) In (7.5) the multiplications $Q_1 L^\# Q$ were performed; it is to be recalled, however, that Q is a matrix with elements 0, 1 or -1 so that no arithmetic multiplications, only additions were performed. Furthermore (see below) it actually would be necessary only to form the L_1 -part of this product.
- C) In (7.7) L_1 was inverted. (Actually one need only "solve" L_1 , say in the manner of K -partitioning below).

Summing up then, tearing involves inverting two matrices $Y_4^\#$ and L_1 . Now let n denote the number of branches of K (which equals the number of branches of $K^\#$). Let p^1 be the dimension of $H^1(K)$, the first Betti number of K , and $p_1^\#$ the first Betti number of $H^1(K^\#)$. The dimension of $Y_4^\#$ is $n - p_1^\#$ and that of L_1 is $p^1 - p_1^\#$: if K were inverted by the Maxwell node-pair method one would have inverted a transformation of the dimension $n - p^1$ which is *less* than $n - p_1^\#$. How then can it be claimed that it is possible that the method of tearing may require fewer arithmetic operations than the standard methods? The answer is that tearing must be done in such a way that the $Y_4^\#$ to be inverted *split* in some convenient fashion. This depends upon the topology of $K^\#$ as well as on the ohmic tensor. In Secs. 9, 10, 11 we shall exhibit cases where it *does* pay off to tear.

8. *K*-partitioning. We are about to compare in detail the number of operations required to solve a few selected network problems by standard methods, by standard partitioning, by an algebraic form of solving equations suggested by tearing, and by tearing. We shall therefore preface these examples by a few remarks on partitioning and obtaining the general solution to a system of linear equations. See [40].

Let

$$Mx = c \quad (8.1)$$

by the matrix form of a non-singular system of n equations in n unknowns. The usual manner of obtaining the general solution is to compute the inverse of M by one method or another, writing the solution in the form $x = M^{-1}c$. Now to invert M it may be expedient to partition M , but let us instead partition the whole system (8.2) into the form

$$\begin{bmatrix} A & B \\ C & D \end{bmatrix} \begin{bmatrix} u \\ v \end{bmatrix} = \begin{bmatrix} a \\ b \end{bmatrix}, \quad (8.2)$$

where

$$\begin{bmatrix} A & B \\ C & D \end{bmatrix} = M \quad \begin{bmatrix} u \\ v \end{bmatrix} = x \quad \begin{bmatrix} a \\ b \end{bmatrix} = c. \quad (8.3)$$

An easy computation shows that the general solution may then be written as

$$\begin{aligned} v &= R(b - CA^{-1}a), \\ u &= A^{-1}(a - Bv), \end{aligned} \quad R = (D - CA^{-1}B)^{-1}. \quad (8.4)$$

(8.4) is a general solution in the following sense: for arbitrary a and b , v is computed according to the first formula; it is then substituted into the second to give u . This is just as good a form of the general solution as (8.2). If (8.4) is accepted as a legitimate form for the general solution, we see that the only multiplications involved are in the computation of A^{-1} , the formation of $CA^{-1}B$, and finding the inverse of $(D - CA^{-1}B)$. This form of the general solution requires in general significantly less work than finding the straight inverse. Incidentally, if the transformations are multiplied out we obtain the standard formula for the inverse by partitioning (U = identity matrix):

$$\begin{bmatrix} u \\ v \end{bmatrix} = \begin{bmatrix} A^{-1}(U + BRCA^{-1}) & -BR \\ -RCA^{-1} & R \end{bmatrix} \begin{bmatrix} a \\ b \end{bmatrix}. \quad (8.5)$$

The form (8.4) is a purely algebraic trick, simple but useful, suggested by the method of tearing. We shall term this *Kron's method of partitioning* or *K-partitioning*, and will compare it with standard partitioning and with tearing in solving network problems.

The disadvantage of the component solutions found by *K*-partitioning, compared with those found by tearing, is that the former cannot be re-utilized to interconnect the solved system with other systems to form the solution of "supersystems". No topology enters into partitioning a matrix. On the other hand, the component solutions established by tearing represent actual physical systems and consequently all partial inverses can be re-utilized to build up factorized solutions for still larger systems.

Kron has used such sequences of partial structures for pyramiding not only numerical solutions, but also eigen-value of analytical solutions, as well as problems in optimization (largely unpublished).

We shall use throughout von Neumann's rule-of-thumb, that it requires n^3 multiplications to invert a matrix of order n .

9. Tearing versus partitioning: first case history [41]. Consider the network in Fig. 2. Here $n = 6$, $p^1 = 3$. We assume that L is purely resistive, and thus that it can

FIG. 2. Network K.

assume diagonal form. Solution of this by either the mesh or node-pair method requires the inversion of a 3×3 matrix of the form

$$\begin{bmatrix} x & 0 & x \\ 0 & x & x \\ x & x & x \end{bmatrix} \quad \text{"x" means a non-zero element.}$$

According to our adopted rule-of-thumb, this requires 27 multiplications. My computations yield the following results:

Number of multiplications required to solve problem

Tearing	3
K-partitioning	8
Standard partitioning	22
Standard inversion	27

FIG. 3. K and $K^\#$ with bases selected.

Solution of K by tearing. We shall tear K into $K^\#$ as shown on the top of Fig. 3. In the figure for $K^\#$, $1_\#$ for example denotes a "current", a cycle impinging on the two branches which make up the cycle; 1^* indicates a current passing through only the single branch indicated, in the direction shown: this is a 1-chain consisting of this single directed simplex. Similar meanings are attached to the other labels.

First we must solve the $K^\#$ network in the first orthogonal form (6.2). A most economical method of doing this is to start with the completely torn system K^* below and interconnect from K^* to $K^\#$, for L must be given a definition completely in terms of coordinates, and it customarily is given for the K^* system, Fig. 4.

FIG. 4. The completely torn network K^* .

Suppose $Y^* = L^{-1}$ assumes the form

$$Y^* = \begin{bmatrix} Y_{1\cdot} & & & & & 0 \\ & Y_{2\cdot} & & & & \\ & & Y_{3\cdot} & & & \\ & & & Y_{4\cdot} & & \\ & & & & Y_{5\cdot} & \\ 0 & & & & & Y_{6\cdot} \end{bmatrix}.$$

In the K^* system the ohmic transformation is written

$$J^* = Y^* V^*$$

where $J^* = \{J^{1*}, \dots, J^{6*}\}$, $V^* = \{V_{1\cdot}, \dots, V_{6\cdot}\}$ the components related in the obvious way to the symbols of Fig. 4. (J^* and V^* do not denote complex conjugates in this section.)

Let φ be the simplicial map of K^* on $K^\#$, whose induced isomorphism on the groups of 1-chains is

	1*	2*	3*	4*	5*	6*	
1 [#]	1				-1		= P_t
2 [#]	1				-1		
3 [#]	1						
4 [#]	1						
1 _#					1		
2 _#					1		

Matrix of interconnection from K^* to $K^\#$.

We may write this in the form

$$\begin{bmatrix} I^\# \\ i^\# \end{bmatrix} = P_t J^*,$$

where $\{I^\#, i^\#\} = \{I^{1\#}, I^{2\#}, I^{3\#}, I^{4\#}; i^{1\#}, i^{2\#}\}$ and P_t is the matrix shown above. The inverse of these Q 's may be written by inspection, for if

$$P = \begin{bmatrix} U & P_1 \\ 0 & U \end{bmatrix},$$

P_1 arbitrary, the U 's of different size in general it is immediate that

$$P^{-1} = \begin{bmatrix} U & -P_1 \\ 0 & U \end{bmatrix}.$$

Kron has used P_t^{-1} instead of P_t , expressing "old currents in terms of new" and he writes it down by inspection of the network; see interconnection from $K^\#$ to K below. Then

$$V_* = P \begin{bmatrix} E^\# \\ e^\# \end{bmatrix}$$

and so

$$\begin{bmatrix} I^\# \\ i^\# \end{bmatrix} = P_t J^* = P_t Y^* V^* = P_t Y^* P \begin{bmatrix} E^\# \\ e^\# \end{bmatrix}.$$

Written more fully,

$$\begin{bmatrix} I^\# \\ i^\# \end{bmatrix} = \begin{bmatrix} Y_1^\# & Y_2^\# \\ Y_3^\# & Y_4^\# \end{bmatrix} \begin{bmatrix} E^\# \\ e^\# \end{bmatrix},$$

$$E^\# = (Y_1^\#)^{-1} (I^\# - Y_3^\# e^\#).$$

The inversion of $Y_1^\#$ involves two operations: $Y_{1\#}^{-1}$, $Y_{2\#}^{-1}$, for $Y_{3\#}^{-1}$ and $Y_{4\#}^{-1}$ are assumed known. (It is assumed that L and Y are known for the completely torn system.) Let

$$(Y_1^\#)^{-1} = L^\# = \begin{bmatrix} L_{1\#} & & & 0 \\ & L_{2\#} & & \\ & & L_{3\#} & \\ 0 & & & L_{4\#} \end{bmatrix}$$

and $I^\# - Y_3^\# e^\# = I_\#$; we have

$$E^\# = L^\# I_\#. \quad (9.1)$$

Now we are prepared for the interconnection transformation between $K^\#$ and K . In contradistinction to the interconnection between K^* and $K^\#$, we write the "old currents in terms of the new", i.e. in the form (7.1). Referring to Fig. (3), we have

$$\begin{array}{c}
 1' \quad 2' \quad 3' \quad 0 \quad 1 \quad 2 \\
 \begin{array}{c}
 1^\# \\
 2^\# \\
 3^\# \\
 4^\# \\
 1_\# \\
 2_\#
 \end{array}
 \begin{array}{|c|c|c|c|c|c|}
 \hline
 & & & & & \\
 \hline
 1 & & & 1 & & \\
 \hline
 & 1 & & 1 & & 0 \\
 \hline
 & & 1 & 1 & & \\
 \hline
 & & & 1 & & \\
 \hline
 & & & & 1 & \\
 \hline
 & & & & & 1 \\
 \hline
 \end{array}
 = \begin{array}{|c|c|}
 \hline
 Q & O \\
 \hline
 O & U \\
 \hline
 \end{array}
 \end{array}$$

Matrix of interconnection from $K^\#$ to K .

$$\begin{pmatrix} I^\# \\ i^\# \end{pmatrix} = \left(\begin{array}{c|c} Q & O \\ \hline O & U \end{array} \right) \begin{pmatrix} I \\ i^0 \\ i^1 \\ i^2 \end{pmatrix} \quad (9.2)$$

and the corresponding transformation on the cochains is

$$\begin{pmatrix} E \\ e_0 \\ e_1 \\ e_2 \end{pmatrix} = \left(\begin{array}{c|c} Q_i & O \\ \hline O & U \end{array} \right) \begin{pmatrix} E^\# \\ e^\# \end{pmatrix}. \quad (9.3)$$

Thus from (9.3), (9.1) and (9.2)

$$\begin{pmatrix} E \\ e_0 \end{pmatrix} = Q_i E^\# = Q_i L^\# I^\# = Q_i L^\# Q \begin{pmatrix} I \\ i^0 \end{pmatrix}.$$

Now

$$Q_i L^\# Q = \left(\begin{array}{ccc|c} L_{1\#} & & & L_{1\#} \\ & L_{2\#} & & L_{2\#} \\ & & L_{3\#} & L_{3\#} \\ \hline L_{1\#} & L_{2\#} & L_{3\#} & L_{4\#} \end{array} \right) = \begin{pmatrix} L_1 & L_2 \\ L_3 & L_4 \end{pmatrix},$$

where

$$L_4 = L_{1\#} + L_{2\#} + L_{3\#} + L_{4\#},$$

(the formation of $Q_i L^\# Q$ requires zero multiplications) or

$$\begin{pmatrix} E \\ e_0 \end{pmatrix} = \begin{pmatrix} L_1 & L_2 \\ L_3 & L_4 \end{pmatrix} \begin{pmatrix} I \\ i^0 \end{pmatrix}.$$

Remaining is to invert L_4 : this takes one division = one multiplication. Now as with (8.4) we write the general solution in the "factorized" form

$$i^0 = L_4^{-1}(e_0 - L_3 I),$$

$$E = L_1 I + L_2 i.$$

This completes the description of the solution of the K network problem. The method of tearing K utilized here is quite distinct from Kron's method, several lengthy steps are eliminated; both depend, however, on the same fundamental topological principles.

One further remark can be made: as Kron has pointed out, the full affair $Q, L^* Q$ need never be formed; only the piece L_4 , the lower right corner, need be formed. In fact, all that need be stored is:

$$\begin{array}{c} L^* \\ Q \\ L_4 - 1. \end{array}$$

10. Tearing versus partitioning: second example, Poisson-type network. This is a Poisson-type network except that, more generally, we assume that the "resistances" in each branch are different; Figure 10.0 shows the network K above with an indicated basis and a network K_* below into which K is torn, also with an indicated basis. We

FIG. 5. Left— K and basis for $C(K)$. Right— K^* and basis for $C(K^*)$.

assume that L is diagonal for the completely torn network. First we give complete details on our solution of K by tearing.

10.1. Solution of problem by tearing.

10.1A. Solution of the K^* network. It takes fewer operations to solve this network in the second normal form, i.e. we will solve for the "mesh currents", since the principle pieces are of identical character (note carefully that we have not assumed that L is the same for each) we shall compute the number of multiplications for one and then

FIG. 6. Upper left rectangle $K_{\#}^{(1)}$ of $K_{\#}$ and $K_{*}^{(1)}$, $K_{\#}^{(1)}$ completely torn.

multiply the total by 4. To write down the appropriate equations we consider the upper left rectangle $K_{\#}^{(1)}$ of K , let K_{*} be this network completely torn up. Then the matrix of interconnection $K_{*}^{(1)} \rightarrow K_{\#}^{(1)}$ is

	$\alpha^{\#}$	$\beta^{\#}$	$1^{\#}$	$2^{\#}$	$3^{\#}$	$4^{\#}$	$5^{\#}$	
α^{*}	1							
β^{*}		1						
1^{*}	1		1					
2^{*}	-1	1		1				
3^{*}	-1				1			
4^{*}		-1				1		
5^{*}		-1					1	

$= Q$

and if L_{*} for $K_{*}^{(1)}$ is diagonal with elements

$$L_{*}^{(1)} = \{L_{\alpha^{*}}, L_{\beta^{*}}, L_{1^{*}}, L_{2^{*}}, L_{3^{*}}, L_{4^{*}}, L_{5^{*}}\}.$$

Then letting $L_{\alpha^{*}} + L_{1^{*}} + L_{2^{*}} + L_{4^{*}} = L_{\alpha^{\#}}$ and $L_{\beta^{*}} + L_{2^{*}} + L_{3^{*}} + L_{5^{*}} = L_{\beta^{\#}}$, we have

$$L_{\#}^{(1)} = Q L_{*}^{(1)} Q = \left[\begin{array}{cc|cccc} L_{\alpha^{\#}} & -L_{2^{\#}} & -L_{1^{*}} & -L_{2^{*}} & -L_{4^{*}} & & \\ -L_{2^{\#}} & L_{\beta^{\#}} & & & -L_{2^{*}} & -L_{4^{*}} & -L_{5^{*}} \\ \hline -L_{1^{*}} & & L_{1^{*}} & & & & \\ -L_{2^{*}} & & & L_{2^{*}} & & & \\ -L_{4^{*}} & -L_{2^{\#}} & & & L_{3^{*}} & & \\ & -L_{4^{*}} & & & & L_{4^{*}} & \\ & -L_{5^{*}} & & & & & L_{5^{*}} \end{array} \right]$$

Let $L_{\#}^{(1)}$ be written

$$L_{\#}^{(1)} = \left[\begin{array}{c|c} L_{\#1}^{(1)} & L_{\#2}^{(1)} \\ \hline L_{\#3}^{(1)} & L_{\#4}^{(1)} \end{array} \right]$$

The second normal form

$$\begin{pmatrix} e_{\#}^{(1)} \\ E_{\#}^{(1)} \end{pmatrix} = \begin{pmatrix} L_{\#1}^{(1)} & L_{\#2}^{(1)} \\ L_{\#3}^{(1)} & L_{\#4}^{(1)} \end{pmatrix} \begin{pmatrix} i_{\#}^{(1)} \\ I_{\#}^{(1)} \end{pmatrix}$$

requires first the inversion of $L_{\#1}^{(1)}$. For simplicity (and with no loss of generality) we assume $e_{\#}^{(1)} = 0$.

Then

$$E_{\#}^{(1)} = [L_{\#4}^{(1)} - L_{\#3}^{(1)}(L_{\#1}^{(1)})^{-1}L_{\#2}^{(1)}]I_{\#}^{(1)} = L_{\#(1)}^{\#}I_{\#}^{(1)}.$$

A tally of operations yields:

<i>Operation</i>	<i>Multiplications required</i>
Inversion of $L_{\#1}$	8
Formation of $L_1^{-1}L_2$	12
Formation of $L_3(L_1^{-1}L_2)$	30
	—
Total to solve $K_{\#}^{(1)}$	50

Now assume that we do this for each of the four main pieces of $K^{\#}$: the total number of multiplications is $4 \cdot 50 = 200$ to solve $K_{\#}$. The final solution for $K_{\#}$ is a direct sum of the solutions for each piece and the remaining disjoint pieces, the "pigtailed": for convenience this latter is split into two pieces $L_p^{\#}$ relating to branches labelled 21 through 24 and $L_q^{\#}$ for 25 through 32, $L_p^{\#}$ and $L_q^{\#}$ both being diagonal.

$$\begin{bmatrix} E_{\#}^{(1)} \\ E_{\#}^{(2)} \\ E_{\#}^{(3)} \\ E_{\#}^{(4)} \\ E_{\#}^{(p)} \\ E_{\#}^{(q)} \end{bmatrix} = \begin{bmatrix} L_{\#(1)}^{\#} & & & & & \\ & L_{\#(2)}^{\#} & & & & \\ & & L_{\#(3)}^{\#} & & & \\ & & & L_{\#(4)}^{\#} & & \\ & & & & L_p^{\#} & \\ & & & & & O \\ O & & & & & L_q^{\#} \end{bmatrix} \begin{bmatrix} I_{\#}^{(1)} \\ I_{\#}^{(2)} \\ I_{\#}^{(3)} \\ I_{\#}^{(4)} \\ I_{\#}^{(p)} \\ I_{\#}^{(q)} \end{bmatrix}$$

Further let

$$L_{\lambda}^{\#} = L_{\#(1)}^{\#} \dot{+} \cdots \dot{+} L_{\#(4)}^{\#} \dot{+} L_p^{\#}$$

and

$$M^{\#} = L_{\lambda}^{\#} + L_q^{\#}.$$

This is the solution for $K_{\#}$. Now we interconnect to get the solution for K .

10.1B. The interconnection $K_{\#} \rightarrow K$. Referring to Fig. 5 we see that the pertinent part of the interconnection transformation from $C(K_{\#})$ to $C(K)$ is (we omit the part injecting the cycles of $K_{\#}$ into the cycles of K —it would correspond to an identity matrix):

$$T = \left[\begin{array}{c|c} U & R \\ \hline O & S \end{array} \right]$$

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21	22	23	24	a	b	c	d	e	f	g	h ← new		
1	1																																
2		1																															
3			1																														
4				1																													
5					1																												
6						1																											
7							1																										
8								1																									
9									1																								
10										1																							
11											1																						
12												1																					
13													1																				
14														1																			
15															1																		
16																1																	
17																	1																
18																		1															
19																			1														
20																				1													
21																					1												
22																						1											
23																							1										
24																								1									
25																									1								
26																										1							
27																											1						
28																												1					
29																													1				
30																														1			
31																															1		
32																																1	
↑																																1	
old																																	

Interconnection tensor $T : CK^{\#} \rightarrow CK$

Going through the usual routine we perform the *rearrangements* $T_1 L_s T$ (this transformation involves at most addition, and actually need not be completely carried out—only the lower corner—the rest can remain in factorized form, *a la* Kron, see Sec. 8 above).

$$L = T_i M_s T = \left[\begin{array}{cc} L_{\lambda}^* & L_{\lambda}^* R \\ \hline (L_{\lambda}^* R)_i & N \end{array} \right] \quad N = R_i L_{\lambda}^* R + S_i L_q^* S.$$

Again it will be observed that the formation of L involves no multiplication; N is the only "piece" of the transformation L that we must compute explicitly anyhow.

The equation for K thus reads

$$\begin{pmatrix} E \\ - \\ o \end{pmatrix} = \begin{pmatrix} L_{\lambda}^* & L_{\lambda}^* R \\ \hline (L_{\lambda}^* R)_i & N \end{pmatrix} \begin{pmatrix} I \\ - \\ i \end{pmatrix}.$$

The *final remaining step* is the "solution" of N .

10.1C. *The elimination of the newly created mesh currents or the "solution" of N .*

Now N is of the form

$$N = \begin{array}{c} \begin{array}{cccccccc} & a & b & c & d & e & f & g & h \end{array} \\ \begin{array}{l} a \\ b \\ c \\ d \\ e \\ f \\ g \\ h \end{array} \end{array} \begin{array}{|cccc|cccc} \hline x & x & x & & & & & x & x \\ x & x & x & x & & & & & x \\ x & x & x & x & x & & & & \\ & x & x & x & x & x & & & \\ \hline & & & x & x & x & x & x & \\ & & & & x & x & x & x & \\ x & & & & & x & x & x & x \\ x & x & & & & & x & x & x \\ \hline \end{array} = \left[\begin{array}{c|c} N_1 & N_2 \\ \hline N_3 & N_4 \end{array} \right]$$

which we partition as indicated. Again, we do not compute the inverse of N but we compute the factorized form of the solution (Sec. 8). We tally the results, the method already having been explained by earlier detailed examples.

Operation	Multiplications required
Inversion of N_1	56
$N_3 N_1^{-1} N_2$	48
Inversion of $(N_4 - N_3 N_1^{-1} N_2)$	64

Total number of multiplications to solve N in factorized form 168 (as compared with 512 if N were inverted by standard methods).

10.1D. *Final tally of number of operations required by the method of tearing here employed.*

A. Solution of K_s network	200
C. Solution of N , the elimination of the cycles created by the interconnection	168
<hr/>	
Total number of multiplications required by tearing solution	368

Next we discuss briefly a partitioning type of solution of K .

10.2. Solution of K by K -partitioning. Let us now refer to the original network K . We shall consider it in its mesh-equivalent form, that is, we "invert" the isomorphism (Fig. 1) of $H^1(K) \xrightarrow{L'} H_1(K)$, since L' is 16×16 whereas Y' is 24×24 . Of many bases tried, the following checkerboard arrangement seemed to be the best.

a	i	b	j
n	c	p	d
e	o	f	k
m	g	l	h

FIG. 7. Checker board basis for $H^1(K)$.

The transformation L' for this basis assumes the following form, which is partitioned as indicated

	a	b	c	d	e	f	g	h	i	j	k	l	m	n	o	p
a	x								x						x	
b		x							x	x						x
c			x						x					x	x	x
d				x						x	x					x
e					x								x	x	x	
f						x					x	x			x	x
g							x					x	x		x	
h								x			x	x				
i	x	x	x						x							
j		x		x						x						
k				x		x		x			x					
l							x	x	x			x				
m					x		x						x			
n	x		x		x										x	
o			x		x	x	x									x
p		x	x	x		x										x

$$= \left[\begin{array}{c|c} A & B \\ \hline C & D \end{array} \right]$$

"x" indicates the presence of a non-zero element.

FIG. 8. L' for checkerboard basis.

Here is the tally of operations:

<i>Operation</i>	<i>Multiplications required</i>
A^{-1}	9
$CA^{-1}B$	98
$(D - CA^{-1}B)^{-1}$	<u>512</u> [($D - CA^{-1}B$) is full]

Total number of multiplications required solving as mesh equivalent network using K -partitioning 618

Next we see how many additional operations would be required if the actual inverse of L' were computed by standard partitioning.

10.3. Solution of K by standard partitioning. Now we must add to the above total of 618 the number of multiplications needed to form the inverse matrix: [see (8.5)].

Multiplications required to reconstruct actual inverse of L' .

<i>Operation</i>	<i>Multiplications required</i>
$R(CA^{-1})$ $8(24) =$	192 [(CA^{-1}) has 24 non-zero elements]
$B(RCA^{-1})$	192
$A(U + BRCA^{-1})$ $8^3 =$	512
BR	<u>192</u>
Total	1079

Thus for standard partitioning the number of multiplications required is $618 + 1079 =$ 1697 = number of multiplications required by standard partitioning.

10.4. Finally if one simply solved K by the most naïve method, by inverting L' by standard methods, then $16^3 = 4096$ multiplications are required

Final Tally

Multiplications required for solving K by various methods.

Tearing	368
K -partitioning	618
Standard partitioning	1697
Standard inversion methods	4096

It will be remarked that the ohmic transformation L in this example was *not* assumed to act identically on the four principal pieces of K_s (see Fig. 5) and thus the solutions for each of the pieces had to be solved separately. In the next section we shall consider the case when L *does* act identically on the four separate pieces. It will turn out that the method of tearing can take better advantage of these symmetries than can partitioning, even K -partitioning; tearing being a topological method can better accommodate to a topological situation than partitioning, a purely algebraic device.

11. Tearing versus partitioning: third case history. Assume now for the network problem of Sec. 10, that L acts in an identical fashion on the four principal pieces of K_s . If we considered K as an electrical network, then we would assume that the imped-

ances of corresponding branches in these pieces are identical. We shall enquire as to how each of the methods can profit from this symmetry.

11.1. Tearing. Referring to 10A, to solve the piece $K_{\#}^{(1)}$ required 50 multiplications, we make four copies of this; then we will assume that any degree of symmetry inherited by N from the symmetry cannot be taken advantage of, so that, as in 10.1C, the inversion of N requires 168 multiplications.

$$\text{Grand total for tearing} = \boxed{218}$$

11.2. Solution by K-partitioning. A. For the checkerboard basis. Here unfortunately the checkerboard basis, Fig. 7, cannot take especial advantage of this symmetry in L : the inversion of A , Fig. 8, requires 2 instead of 8 multiplications and otherwise the counts are the same so that for this new problem, checkerboard basis with K -partitioning:

$$\boxed{612}$$

B. For another basis. Let us choose the basis shown below

1	2	14	3
13	19	10	4
8	12	11	15
7	16	6	5

FIG. 9. A basis for partitioning.

Then L' assumes the form shown in Fig. 10, which we partition as indicated.

Count of multiplications by K-partitioning

$$\begin{array}{rcl} A^{-1} & 2^3 & = 8 \\ CA^{-1} & & 24 \\ (CA^{-1})B & & 33 \\ (D - CA^{-1}B)^{-1}: & 8^3 & = \boxed{512} \end{array}$$

$$\text{Total} \quad \boxed{577}$$

If L were *not* the same on each of the $K_{\#}^i$ then the inversion of A for the basis selected here would have been 32, for a grand total of 611; thus this basis, shown in 11.3A, would have been better for the problem of Sec. 10 than that of 10.2A.

We may assume that the multiplications required to get the inverse from this form is the same as for the problem in Sec. 10.3. Thus

11.3. Number of multiplications required for standard partitioning is

$$577 + 1079 = \boxed{1656}$$

11.4. Standard inversion is still, of course, $\boxed{4096}$.

	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16
1	x	x											x			
2	x	x							x					x		
3			x	x										x	x	
4			x	x					x						x	
5					x	x									x	
6					x	x				x						x
7							x	x								x
8							x	x				x	x			
9		x							x	x		x	x			
10				x					x	x	x			x		
11						x				x	x	x			x	
12							x		x		x	x				
13	x							x	x				x			
14		x	x							x				x		
15				x	x						x				x	
16					x	x	x					x				x

$$= \left(\begin{array}{c|c} A & B \\ \hline C & D \end{array} \right)$$
FIG. 10. L' for basis chosen.

Appendix. One very important advantage of tearing over standard methods of solving networks is the fact that the solution developed for a component of the torn system is in fact a perfectly complete solution for this subsystem *in itself*. Thus regardless of how the subsystems are to be connected together, their individual solutions are completely useable. This is one advantage which solving a network by partitioning Y' (or L') for a given fixed system cannot enjoy. For the partitioning is performed on the Y' for a given *fixed* system; in the Y' the interactions both through the topological connections and through the "electromagnetic couplings" may be rather thoroughly scrambled: partitioning Y' cannot sort these effects out.

Another way of contrasting tearing with standard methods is this: A *network problem* consists of a pair (L, K) , an ohmic tensor L is a complex K compatible with L . In tearing one seeks another network problem (L^*, K^*) in which the tensor L^* (or Y') *splits* in a convenient manner. From the solution of this network problem one then deduces the solution for the original problem. In solving the network problem (L, K) by standard methods, one operates *only* on L' or Y' for this given network problem; for instance, one partitions Y' in the most expedient manner. Both of these advantages may be exceedingly important in the solution of very large physical problems.

The examples of this paper exhibit definite numerical advantages in tearing but, more importantly, they carry forward and improve on the mechanics of Kron's method of tearing.

BIBLIOGRAPHY

1. H. B. Phillips and N. Wiener, *Nets and the Dirichlet problem*, J. Math. and Phys. 2, 105-124 (1923)
2. L. A. Lyusternik, *On electrical modelling of symmetric matrices*, Uspekhi Matem. Nauk (N.S.) 41, 198-200 (1949)
3. G. Kron, *Numerical solution of ordinary and partial differential equations by means of equivalent circuits*, J. Appl. Mech. 16, 172-186 (1945)
4. G. Kron, *Equivalent circuit of the field equations of Maxwell*, Proc. IRE 32, 289-299 (1944)
5. G. Kron, *Electric circuit models of the Schrödinger equation*, Phys. Rev. 67, 39-43 (1945)
6. G. Kron, *Equivalent circuits of the elastic field*, J. Appl. Mech. 11, A149-161 (1944)
7. G. Kron, *Equivalent circuits of compressible and incompressible fluid flow fields*, J. Aero. Sci. 12, 221-231 (1945)
8. G. Kron, *A set of principles to interconnect the solutions of physical systems*, J. Appl. Phys. 24, 965-980 (1953)
9. G. Kron, *Solution of complex non-linear plastic structures by the method of tearing*, J. Aero. Sci. 23, 557-562 (1956)
10. R. von Mises, *On network methods in conformal mapping and in related problems. Construction and application of conformal maps*, U. S. Dept. of Commerce, Natl. Bur. Standards, Appl. Math. Ser. 18, 1-6 (1952)
11. G. D. Birkhoff and J. B. Diaz, *Non-linear network problems*, Quart. Appl. Math. 13 (4) 431-443 (1956)
12. A. K. Oppenheim, *Radiation analysis by the network method*, Trans. ASME 78, 75-735 (1956)
13. A. K. Oppenheim, *The engineering radiation problem—an example of the interaction between engineering and mathematics*, Z. angew. Math. u. Mech. 36, 81-92 (1956)
14. F. H. Branin, *Kron's method of tearing and its applications*, Proc. 2nd Midwest Symp. Circuit Theory, Mich. State U., 1956, p. 2.1-2.79
15. G. Kirchhoff, *Ueber die Auflösung der Gleichungen, auf welche man bei der Untersuchung der linearen Vertheilung galvanischer Ströme führt wird*, Poggendorf's Ann. Physik u. Chemie 72, 497-508 (1847)
16. J. C. Maxwell, *Electricity and Magnetism*, vol. 1, p. 406, Oxford Univ. Press, 1892, 3rd edition
17. H. Weyl, *Repartition de corriente et uno red conductora*, Revista matematica, Hispano-Americana 5, 153-164 (1923)
18. B. Eckmann, *Harmonische Funktionen und Randwert Aufgaben in einem Komplex*, Comm. Math. Helvetici 17, 240-255 (1944-1945)
19. G. Kron, *Tensor analysis of rotating machinery. I*, Presented winter convention of AIEE (1933)
20. G. Kron, *Non-Riemannian dynamics of rotating electrical machinery*, J. Math. and Phys. 12, 103-194 (1934)
21. G. Kron, *The application of tensors to rotating electrical machinery*, General Electric Review, Schenectady, New York, 1938
22. G. Kron, *Tensor analysis of networks*, John Wiley & Sons, Inc., New York, 1939
23. G. Kron, *Analyse tensorielle appliquée a l'Art de l'Ingénieur*, Bulletin de l'Association des Ingénieurs Electriciens sortis de l'Institut Electrotechnique Montefiore, No. 9, Sept. 1936; No. 10, Oct. 1936; No. 1, Jan. 1937; No. 2, Feb. 1937
24. B. Hoffman, *A mathematical interpretation of some work of Gabriel Kron*, Mimeographed lectures delivered at Brown University, Nov. 12-13, 1943
25. B. Hoffman, *Kron's method of subspaces*, Quart. Appl. Math. vol. 2, 218-231 (1944)
26. B. Hoffman, *Kron's non-Riemannian electrodynamics*, Review Modern Physics 21, Commemorating Einstein's 70th birthday 21, 535-540 (1949)
27. J. L. Synge, *The fundamental theorem of electrical networks*, Quart. Appl. Math. 9, 113-127 (1951)
28. le Corbeiller, *Matrix analysis of networks*, John Wiley & Sons, Inc., New York, 1950
29. J. P. Roth, *An application of algebraic topology to numerical analysis: Kron's method I*, Bull. Am. Math. Soc. 61, 183 (1955)
30. J. P. Roth, *An application of algebraic topology to numerical analysis: Kron's method II*, Bull. Am. Math. Soc. 61, 183 (1955)

31. J. P. Roth, *An application of algebraic topology to numerical analysis: I. On the existence of a solution to the network problem*, Proc. Natl. Acad. Sci. **41**, 518-521 (1955)
32. J. P. Roth, *An application of algebraic topology to numerical analysis: II. The validity of Kron's method of tearing*, Proc. Natl. Acad. Sci. **41**, 599-600 (1955)
33. J. P. Roth, *An application of algebraic topology to numerical analysis: III. Three theorems on networks*, Bull. Am. Math. Soc. **62**, 32 (1956)
34. H. Bode, *Ein elektrisches Gerät zum Lösen von Systemen linearer Gleichungen*, Z. angew. Math. u. Mech. **17**, 213-223 (1937)
35. G. Kron, *Electric circuit models for the vibration spectrum of polyatomic molecules*, J. Chem. Phys. **14**, 19-31 (1946)
36. G. Kron, *Tearing and interconnecting as a form of transformation*, Quart. Appl. Math. **13**, 147-159 (1955)
37. G. Kron, *Electric-circuit models of the nuclear reactor*, AIEE Trans. 1954
38. S. Eilenberg and N. E. Steenrod, *Foundations of algebraic topology*, Princeton Univ. Press, Princeton, N. J., 1952
39. H. Cartan, *Lectures on algebraic topology. Mimeographed lecture notes*, Harvard University, 1949-1950
40. J. P. Roth, *A method for finding the general solution to an arbitrary non-singular system of linear equations involving $n^3/2$ multiplications*, The Institute for Advanced Study, ECP Tech. Rept. 56-01, Jan. 1956 (To appear in *Math. tables and other aids to computation*)
41. J. P. Roth, *An application of algebraic topology to numerical analysis: IV. Tearing versus partitioning*, Bull. Am. Math. Soc. **62**, 45 (1956)