On Designs of Maximal $(+1, -1)$ -Matrices of Order $n \equiv 2 \pmod{4}$. II*

By C. H. Yang

Abstract. Finding maximal $(+1, -1)$ -matrices M_{2m} of order $2m$ (with odd m) constructible in the standard form

$$\begin{pmatrix} A & B \\ -B^T & A^T \end{pmatrix}$$

is reduced to the finding of two polynomials $C(w)$, $D(w)$ (corresponding to the circulant submatrices A , B) satisfying

$$(*) \quad |C(w)|^2 + |D(w)|^2 = \frac{1}{2}(m-1),$$

where w is any primitive m th root of unity. Thus, all M_{2m} constructible by the standard form (see [4]) can be classified by the formula (*). Some new matrices M_{2m} for $m = 25, 27, 31$, were found by this method. ■

Let M_{2m} be a maximal $(+1, -1)$ -matrix of order $2m$ and let $S = ((s_i))$ be the circulant matrix of order m with the first row entries s_i ($0 \leq i \leq m-1$), all zero but $s_1 = 1$.

When m is odd, it is known that (for $m \leq 27$, except $m = 11, 17$; see [1]–[4]), M_{2m} can be constructed by the following matrix:**

$$(1) \quad R = \begin{pmatrix} A & B \\ -B^T & A^T \end{pmatrix}, \quad \text{where } A = \sum_{k=0}^{m-1} a_k S^k, B = \sum_{k=0}^{m-1} b_k S^k \text{ with}$$

a_k and b_k , 1 or -1 , and T indicates the transposed matrix. Then the gramian matrix of R becomes

$$RR^T = \begin{pmatrix} P & 0 \\ 0 & P \end{pmatrix},$$

where P is equal to

$$(2) \quad AA^T + BB^T = 2 \left(mI + \sum_{k=1}^{m-1} S^k \right),$$

where I is the identity matrix of order m .

By applying to the both sides of (2) the transformation L which transforms S into a diagonal matrix $W = [w_1, \dots, w_m]$ with w_j , all distinct m th roots of unity, (namely, $L(S) = U^* S U = W$, where U is unitary and $*$ indicates the conjugate transpose; see [5]) we obtain

Received July 10, 1967, revised August 5, 1968.

* This research was supported by Faculty Research Fellowship of The Research Foundation of The State University of New York.

** For $n = 25$, without circulancy of submatrices A and B , see [2]; also see Addition of this paper.

(3)
$$A(w)A(w^{m-1}) + B(w)B(w^{m-1}) = 2\left(m + \sum_{k=1}^{m-1} w^k\right)$$

where

$$A(w) = \sum_{k=0}^{m-1} a_k w^k, B(w) = \sum_{k=0}^{m-1} b_k w^k,$$

and w is any m th root of unity.

Since w and w^{m-1} are conjugate to each other, (3) is also equivalent to

(4)
$$|A(w)|^2 + |B(w)|^2 = 2\left(m + \sum_{k=1}^{m-1} w^k\right).$$

Let p and q be respectively the numbers of -1 's in each row of A and B . By replacing 1 by 0 and -1 by 1 in A and B and performing the similar process as above, we obtain the following formula corresponding to (4).

(5)
$$|C(w)|^2 + |D(w)|^2 = p + q + r \sum_{k=1}^{m-1} w^k,$$

TABLE I

m	$C(w)$	$D(w)$	N_A	N_B	N
3	0	1	1	1	1
5	1	1	1	1	1
7	1	$1 + w + w^3$	1	1	1
9	$1 + w$	$1 + w^2 + w^5$	3	3	3
13	$1 + w + w^3 + w^9$	$1 + w_0 + w_0^3 + w_0^9$	2	2	4
	$1 + w + w^4$	$1 + w + w^2 + w^4 + w^7 + w^9$	2	4	4
		or $1 + w + w^3 + w^5 + w^7 + w^8$			
15	$1 + w + w^4 + w^6$	$1 + w + w^3 + w^4 + w^8 + w^{10}$	4	8	8
		or $1 + w + w^3 + w^5 + w^8 + w^9$	2	2	2
	$1 + w + w^4 + w^{10}$	$1 + w + w^3 + w^5 + w^7 + w^8$			
19	$1 + w + w^3 + w^5 + w^8 + w^9$	$1 + w + w^3 + w^7 + w^9 + w^{10} + w^{14}$	9	9	9
	$1 + w + w^2 + w^4 + w^7 + w^{12}$	$1 + w + w^3 + w^4 + w^8 + w^{10} + w^{14}$	6	6	12
	or $1 + w + w^3 + w^{12} + w^{14} + w^{15}$	or $1 + w + w^3 + w^5 + w^9 + w^{10} + w^{16}$			
	$1 + w + w^2 + w^3 + w^6 + w^{12}$	$1 + w + w^5 + w^7 + w^9 + w^{12} + w^{15}$	9	9	9
	$1 + w + w^2 + w^3 + w^7 + w^{12}$	$1 + w + w^3 + w^6 + w^8 + w^{12} + w^{16}$	9	18	18
		or $1 + w + w^3 + w^7 + w^{11} + w^{14} + w^{16}$			

When $m = 27$, we have

$$\begin{aligned} C(w) &= 1 + w + w^2 + w^3 + w^6 + w^{10} + w^{12} + w^{15} + w^{23}, \\ D(w) &= 1 + w + w^2 + w^5 + w^7 + w^9 + w^{10} + w^{17} + w^{20} + w^{21} + w^{23}. \end{aligned}$$

When $m = 31$, we have

$$\begin{aligned} C(w) &= 1 + w + w^2 + w^3 + w^4 + w^8 + w^{13} + w^{19} + w^{23} + w^{26}, \\ D(w) &= 1 + w + w^2 + w^3 + w^6 + w^7 + w^{10} + w^{12} + w^{14} + w^{15} + w^{17} + w^{18} \\ &\quad + w^{24} + w^{26} + w^{28}. \end{aligned}$$

Mathematics Department
State University College
Oneonta, New York 13820

1. H. EHLICH, "Determinantenabschätzungen für binäre Matrizen," *Math. Z.*, v. 83, 1964, pp. 123–132.
2. C. H. YANG, "Some designs for maximal $(+1, -1)$ -determinant of order $n \equiv 2 \pmod{4}$," *Math. Comp.*, v. 20, 1966, pp. 147–148. MR 32 #5534.
3. C. H. YANG, "A construction for maximal $(+1, -1)$ -matrix of order 54," *Bull. Amer. Math. Soc.*, v. 72, 1966, p. 293. MR 32 #5678.
4. C. H. YANG, "On designs of maximal $(+1, -1)$ -matrices of order $n \equiv 2 \pmod{4}$," *Math. Comp.*, v. 22, 1968, pp. 174–180.
5. J. WILLIAMSON, "Hadamard's determinant theorem and the sum of four squares," *Duke Math. J.*, v. 11, 1944, pp. 65–81. MR 5, 169.